


Type	V_R max (V)	I_O I_F^* max (mA)	V_F / I_F max (V) (mA)	I_R / V_R max (μ A) (V)	$I_R / V_R / T_{amb}$ max (μ A) (V) ($^{\circ}$ C)	Case
------	---------------------	---------------------------------	--------------------------------	--------------------------------------	--	------

tungsten point contact - general purpose
 $T_{amb} = 25^{\circ}\text{C}$
pointe tungstene - usage général

1N 34	50	30	1	5	30	10						
1N 48	70	50	1	4	830	50						
1N 54 A	50	30	1	5	7	10	100	50	25			
1N 63	100	50	1	4	50	50	25	10	25			
1N 65	70	50	1	2,5	200	50						
1N 81	40	40	1	3	10	10	100	40	25			
1N 126 A	60	30	1	5	800	50	50	10	25			
1N 127 A	100	30	1	3	300	50	25	10	25			
1N 128	40	30	1	3	10	10						
1N 198	80	30	1	4	50	50	250	50	75			
1N 933	80	30	1	4	80	80	250	50	75			
AA 117	90	30	3,3	30	280	100	250	75	60			
AA 118	90	30	2,6	30	250	100	250	75	60			
AA 131	25	30	1	1,7	220	25						
AA 132	100	30	1,8	10	120	60						
SFD 108	100	50*	1	5	7	10	380	100	55			


 DO 7
(CB-26)

Type	V_R max (V)	I_O max (mA)	V_F / I_F max (V) (mA)	I_R / V_R max (μ A) (V)	$I_R / V_R / T_{amb}$ max (μ A) (V) ($^{\circ}$ C)	t_{rr} / I_F (ns) (mA)	Case
------	---------------------	----------------------	--------------------------------	--------------------------------------	--	-----------------------------	------

tungsten point contact - switching
 $T_{amb} = 25^{\circ}\text{C}$
pointe tungstene - commutation


26 P 1	50	50	1	5	50	50	25	10	25	500	30	
FS 36	30	30	2	30	10	10	250	30	25	300	10	
SFD 105	30	30	1	5	30	10	500	30	55	160	10	


 DO 7
(CB-26)

Type	V_R max (V)	I_O max (mA)	V_F / I_F max (V) (mA)	I_R / V_R max (μ A) (V)	$I_R / V_R / T_{amb}$ max (μ A) (V) ($^{\circ}$ C)	Case
------	---------------------	----------------------	--------------------------------	--------------------------------------	--	------

tungsten point contact - detection
 $T_{amb} = 25^{\circ}\text{C}$
pointe tungstene - détection

1N 541	30	35	1	4	18	10	500	45	60			
1N 542 (1)	30	35	1	4	18	10	500	45	60			
AA 143 S	25	60	0,52	15	100	25						
AA 113 (1)	60	10	1	3,5	120	30	500	60	25			
AA 119 (1)	30	35	1	4	18	10	500	45	60			
SFD 107												
AA 130	10	20	1	4,5	220	10						


 DO 7
(CB-26)


 (1) 2.AA 113 : matched pair of AA 113
 2.AA 113 : Deux AA 113 appariées

 2.AA 119 : matched pair of AA 119
 2.AA 119 : Deux AA 119 appariées

 1N 542 : Sold by matched pairs (2 $\times$ 1N 542)
 1N 542 : Livrées par paires appariées (2 $\times$ 1N 542)

tungsten point contact - video detection
 $T_{amb} = 25^{\circ}\text{C}$
pointe tungstene - détection vidéo

1N 60	25	30	0,5	0,375	200	10						
1N 64	15		1	3	25	10						
1N 87	23	30	0,25	0,1	10	1,5	650	20	60			
1N 295	40	35	0,5	0,375	200	10						
AA 112	20	20	1	6	150	20	250	20	55			
AA 116	20	20	0,25	0,1	150	20						
AA 121	25	30	1	7	12	2						
AA 123	18	30	1	4	1,5	1						
SFD 104												
AA 114	25	20	1	6	400	25	500	25	55			
SFD 106	25	30	1	5	10	1,5	200	25	25			
SFD 111	25	30	1	6	6	2	150	20	25			
SFD 112	40	20	1	2,7	12	5	220	25	25			


 DO 7
(CB-26)